

Short Message Service Error Code Product Introduction





Copyright Notice

©2013-2018 Tencent Cloud. All rights reserved.

Copyright in this document is exclusively owned by Tencent Cloud. You must not reproduce, modify, copy or distribute in any way, in whole or in part, the contents of this document without Tencent Cloud's the prior written consent.

Trademark Notice



All trademarks associated with Tencent Cloud and its services are owned by Tencent Cloud Computing (Beijing) Company Limited and its affiliated companies. Trademarks of third parties referred to in this document are owned by their respective proprietors.

Service Statement

This document is intended to provide users with general information about Tencent Cloud's products and services only and does not form part of Tencent Cloud's terms and conditions. Tencent Cloud's products or services are subject to change. Specific products and services and the standards applicable to them are exclusively provided for in Tencent Cloud's applicable terms and conditions.



Error Code

Last updated: 2018-08-24 15:54:56

1. Error Codes for SMS Delivery

Error Code	Reason	Solution
1001	sig verification failed.	Check the sig format of the API.
1002	Text/Voice SMS contains sensitive words.	A response packet including these sensitive words is returned. Delete these words and send again.
1003	sig field is missing or left empty in request packet.	Comply with the specifications in A PI description.
1004	Failed to resolve request packet. This is generally because the specifications in API description is not complied with.	Refer to 1004 error description.
1006	No permission to request. For example, no ext ended code permission, etc.	Check error message. For other qu estions, provide the mobile numbe r from which you failed to send SM S message when you contact SMS Helper.
1007	Other error	Check error message. For other questions, provide the mobile number from which you failed to send SM S message when you contact SMS Helper.
1008	Request to send text/voice SMS timed out.	Rare occurrence. Try again.
1009	Request ip is not on the whitelist.	Verification of request's source ip has been configured, but the curre nt request ip is not found in the configuration list. If necessary, contact SMS Helper.
1011	REST API does not exist.	Check REST API description.



Error Code	Reason	Solution
1012	Signature format is incorrect or signature is n ot approved.	Signature is a combination of 2-8 c haracters comprised of English lett er and numbers only. If the signature format is correct, check whether it is approved.
1013	Text/Voice SMS hits the delivery frequency lim it policy.	You can adjust the delivery freque ncy limit policy for text SMS messa ges on the console. For voice SMS messages, contact SMS Helper.
1014	Template is not approved or request content does not match the approved template content.	Refer to 1014 error description.
1015	Number on the blacklist. This is generally bec ause you unsubscribed from the SMS service or hit the operator's blacklist.	Contact SMS Helper to solve the problem.
1016	Incorrect number format	Check whether the format of the mobile number from which you send text/voice SMS is correct.
1017	The content of the requested SMS is too long.	The length of SMS content exceed s the limit. Adjust the length of SM S content.
1018	The format of voice verification code is incorr ect.	Comply with the specifications in the API description.
1019	sdkappid does not exist.	
1020	sdkappid is disabled.	This sdkappid is unavailable. If nec essary, contact SMS Helper.
1021	The time when the request was initiated is exc eptional. This is generally because the differe nce between the time on your server and that on the Tencent Cloud server exceeds 10 minut es.	Check whether the server time and the time field in the API are norma I.
1022	The number of business SMS messages sent e very day exceeds the upper limit.	You can adjust the SMS delivery fr equency limit policy on the consol e.



Error Code	Reason	Solution
1023	The number of SMS messages sent from a sin gle mobile number within 30 seconds exceeds the upper limit.	You can adjust the SMS delivery fr equency limit policy on the consol e.
1024	The number of SMS messages sent from a sin gle mobile number within 1 hour exceeds the upper limit.	You can adjust the SMS delivery fr equency limit policy on the consol e.
1025	The number of SMS messages sent from a sin gle mobile number every day exceeds the upp er limit.	You can adjust the SMS delivery fr equency limit policy on the consol e.
1026	The number of the same SMS messages sent f rom a single mobile number exceeds the upp er limit.	You can adjust the SMS delivery fr equency limit policy on the consol e.
1029	Time constraint on delivering marketing SMS messages.	To avoid disturbing users, marketin g SMS messages are only allowed t o be sent between 8:00 and 22:00.
1030	This request is not supported.	
1031	Insufficient balance in SMS package.	Purchase package.
1032	Individual user does not have the permission t o send marketing SMS messages.	
1033	Service is suspended due to arrears.	You can top up your account by lo gging in to Tencent Cloud to pay o ff the overdraft.

2 Error Codes for Status Report

Error Code	Category	Reason	Solution
DELIVRD	Three m ajor oper ators	SMS message is received successfully.	None
UNDELIVRD	Three m ajor oper ators	Invalid number, out-of-service ph one or powered-off phone	None



Error Code	Category	Reason	Solution
MX:0003	Three m ajor oper ators	The number of MT SMS messages sent from a single mobile number on the day exceeds the limit.	Contact SMS Helper to remove th e limit.
REJECTD	Three m ajor oper ators	SMS message is rejected for some reason.	Verify whether the mobile device i s normal.
MX:0012	Three m ajor oper ators	The target number is on the custo mer unsubscription blacklist.	The user is added to the blacklist after replying to the unsubscription SMS massage.Contact SMS Helper to remove the number from the blacklist.
MX:0011	Three m ajor oper ators	The target number is on the black list of one-year prohibition.	The blacklist of one-year prohibiti on lists the phone numbers of use rs who file malicious complaints a nd of those who make complaints for multiple times.
BWLIST _00 6	Three m ajor oper ators	Gateway blacklist	Contact SMS Helper to solve the p roblem through communication.
TE:0003	Three m ajor oper ators	The number of MT SMS messages sent from a single mobile number on the day exceeds the limit.	Contact SMS Helper to remove th e limit.
TE:0014	Three m ajor oper ators	Manual verification failed	Contact SMS Helper for communication.
TE:0002	Three m ajor oper ators	Failed to submit SMS messages to gateway	None
TD:0001	Three m ajor oper ators	Gateway blacklist	Contact SMS Helper for communication.
TD: 0004	Three m ajor oper ators	Suspected of fishing. Make a check.	



Error Code	Category	Reason	Solution
TD:19	Three m ajor oper ators	Number on the blacklist	Contact SMS Helper to solve the p roblem through communication.
TD:18	Three m ajor oper ators	Number from unknown operator	None
UNDELIV	China M obile	Invalid number, out-of-service ph one or powered-off phone	Verify whether the mobile device i s normal.
MI:0013	China M obile	Out-of-service phone or powered -off phone	None
MN:0001	China M obile	Invalid number, out-of-service ph one or powered-off phone	Verify whether the mobile device is normal.
MK:0012	China M obile	Invalid number	Verify whether the mobile device i s normal.
MK:0005	China M obile	Whether the No. 21 value-added s ervice attribute of the account op ening data of the target user is su pported.	If the number status is normal, the user can contact local operator's c ustomer service to confirm wheth er the SMS service is enabled.
MK:0005	China M obile	You are prohibited from calling. Y our SMS service is disabled. The er ror code is 5 in maintenance and t est console and 13 in ETSI GSM 09 02 protocol.	Verify whether the mobile device is normal.
MK:0000	China M obile	Invalid number	Verify whether the mobile device is normal.
MN:0054	China M obile	Invalid number, out-of-service ph one or powered-off phone	Verify whether the mobile device i s normal.
MK:0001	China M obile	MK0001 means that this number is not found by HLR. The status ret urned from SMC is unrecognized number, indicating that the SMS message is sent to a wrong number.	Verify whether the mobile device is normal.



Error Code	Category	Reason	Solution
EXPIRED	China M obile	SMS message expired	Failed to receive SMS message du e to no response from the mobile device after a long period of time.
MI:0024	China M obile	Out-of-service phone or powered -off phone	None
MI:0011	China M obile	Invalid number, out-of-service ph one or powered-off phone	None
MC:0151	China M obile	Invalid number, out-of-service ph one or powered-off phone	None
IC:0001	China M obile	Out-of-service phone or powered -off phone	None
MI:0029	China M obile	Out-of-service phone or powered -off phone	None
MI:0005	China M obile	Invalid number, out-of-service ph one or powered-off phone	None
MK:0004	China M obile	Out-of-service phone or powered -off phone	None
MI:0000	China M obile	Invalid number, out-of-service ph one or powered-off phone	None
MI:0022	China M obile	China Mobile gateway internal err or	Verify whether the mobile device i s normal.
IA:0054	China M obile	Failed to receive response messag e due to timeout	Verify whether the mobile device i s normal. Restart the phone and tr y again.
MC:0055	China M obile	Failed to send SMS message beca use user's phone is out of the serv ice area or the memory is full	Verify whether the mobile device i s normal.
MN:0059	China M obile	Invalid number, out-of-service ph one or powered-off phone	Verify whether the mobile device i s normal.
MN:0036	China M obile	User's phone was out of the servic e area.	Verify whether the mobile device i s normal. SMS delivery failed beca use the user is busy.



Error Code	Category	Reason	Solution
MI:0004	China M obile	Invalid number, out-of-service ph one or powered-off phone	None
MI:0020	China M obile	Invalid number, out-of-service ph one or powered-off phone	None
MK:0029	China M obile	Temporarily unavailable	Verify whether the mobile device i s normal.
MI:0084	China M obile	Invalid number, out-of-service ph one or powered-off phone	None
MK:0024	China M obile	Failed to send SMS message beca use the target phone is powered off.	Verify whether the mobile device i s normal.
MK00001	China M obile	Invalid number	Verify whether the mobile device i s normal.
MI:0017	China M obile	Invalid number, out-of-service ph one or powered-off phone	None
MK:0015	transacti on	When an SMS message is sent, the e target phone has a software problem in the process of receiving message. For example, after the phone is restarted, the software for processing the SMS message is not initialized to process the message normally.	Verify whether the mobile device is normal.
MN:0029	China M obile	Invalid number, out-of-service ph one or powered-off phone	Verify whether the mobile device i s normal.
IC:0151	China M obile	Invalid number, out-of-service ph one or powered-off phone	Verify whether the mobile device i s normal.
MN:0075	China M obile	Operater's internal error	None
MK:0010	China M obile	Temporarily unavailable	Verify whether the mobile device i s normal.
IC:0015	China M obile	None	



Error Code	Category	Reason	Solution
BEYONDN	China M obile	Operater's internal error	None
MI:0055	China M obile	Invalid number, out-of-service ph one or powered-off phone	None
MI:0010	China M obile	The number has expired	None
MC00151	China M obile	Operater's internal error	None
IC:0055	China M obile	Operater's internal error	None
MB:1078	China M obile	Operater's internal error	Provide the phone number to SM S Helper and submit a ticket to ve rify with operator.
MN00001	China M obile	Operater's internal error	None
ID:0013	China M obile	Operater's internal error	None
MC:0001	China M obile	Unknown error	None
MK: 0017	China M obile	The memory is full.	The space for storing SMS messag es is full. Free up space by clearin g the SMS messages stored in the phone.
MI:0081	China M obile	Operater's internal error	None
DA:0054	China M obile	Failed to receive response messag e due to timeout	Verify whether the mobile device i s normal.
MB:1042	China M obile	The number of SMS messages cac hed in the SMC memory and to b e sent to the target user exceeds t he maximum number of SMS mes sages received by this user.	Check the number of the SMS me ssages sent to the target number in the SMC memory. If the number has reached the maximum number of SMS messages received by the target user, submit again later.



levice i
levice i
levice i
levice i
levice i
levice i
levice i



Error Code	Category	Reason	Solution
MN:0050	China M obile	Invalid number, out-of-service ph one or powered-off phone	Verify whether the mobile device i s normal.
MN:0017	China M obile	SMS message rejected	Verify whether the mobile device i s normal.
MI:0045	China M obile	China Mobile gateway internal err or	None
MN:0055	China M obile	Operater's internal error	None
NOROUTE	China M obile	No route found	None
MI:0036	China M obile	China Mobile gateway internal err or	None
MB:1077	China M obile	User on the blacklist. This is becau se China Mobile keeps a record of the user's malicious complaints.	The user need to communicate wi th China Mobile by calling 10086 to remove the number from the bl acklist.
MI:0020	China M obile	Operater's internal error	None
MI:0022	China M obile	Operater's internal error	None
MN:0053	China M obile	Operater's internal error	None
DB:0505	China M obile	Operater's internal error	None
ID:0070	China M obile	Operater's internal error	None
MX:0002	China M obile	Failed to submit SMS message to the higher channel	None
DB:0141	China M obile	User on the blacklist. This is because the user has filed complaints a gainst China Mobile or MIIT for many times.	Cannot be removed from the blac klist.



Error Code	Category	Reason	Solution
MA:0051	China M obile	Operater's internal error	None
IB:0008	China M obile	Operater's internal error	None
MI00000	China M obile	SMS message has expired in SMC	None
DB:0164	China M obile	Operater's blacklist	None
MI:0013	China M obile	Invalid number	None
DB:0144	China M obile	User on the global blacklist	None
BWLIST	China M obile	Gateway blacklist	Contact SMS Helper to remove the number from the blacklist.
HD:19	China M obile	Gateway blacklist	Contact SMS Helper to remove the number from the blacklist.
MI00020	China M obile	Failed to send SMS message to m obile device (ErrorinMS)	None
MI:0041	China M obile	Operater's internal error	None
MC:0055_00 6	China M obile	Failed to send SMS message beca use user's phone is out of the serv ice area or the memory is full	Verify whether the mobile device i s normal.
MI:0064	China M obile	Operater's internal error	None
ERR_NUM_0 06	China M obile	Target number is incorrect or restricted.	Verify whether the mobile device i s normal.
MI:0057	China M obile	Operater's internal error	None
MI:0056	China M obile	Response timeout	Verify whether the mobile device i s normal.



Error Code	Category	Reason	Solution
MN:0098	China M obile	Operater's internal error	None
MK:0036	China M obile	Unknown error from MSC.	None
MN:0019	China M obile	Operater's internal error	None
MI:0030	China M obile	Operater's internal error	None
MI:0023	China M obile	Operater's internal error	None
MI:0002	China M obile	Operater's internal error	None
MK:0019	China M obile	SMS message termination busines s is not supported for MS.	Verify whether the mobile device i s normal.
IB:0064	China M obile	Powered off	Verify whether the mobile device i s normal.
MB:1026	China M obile	SMC-related parameters (such as MO speed, MT speed, number of SMS messages, number of SMS message entities) have reached the upper limit of License.	Submit the SMS message again la ter.
MK:0055	China M obile	Operater's internal error	None
MK:0066	China M obile	Operater's internal error	None
MI00022	China M obile	The memory of mobile device is full.	Verify whether the mobile device i s normal.
IB:0009	China M obile	Operater's internal error	None
MK:0006	China M obile	Operater's internal error	None



Error Code	Category	Reason	Solution
MK:0053	China M obile	Operater's internal error	None
MK:0023	China M obile	Operater's internal error	None
MK:0045	China M obile	Operater's internal error	None
MC:0055_00 0	China M obile	Failed to send SMS message beca use user's phone is out of the serv ice area or the memory is full	Verify whether the mobile device i s normal.
MA:0054	China M obile	Operater's internal error	Provide the phone number to SM S Helper and submit a ticket to ve rify with operator.
MK:0041	China M obile	Operater's internal error	None
MK:0063	China M obile	Operater's internal error	None
ID:0012	China M obile	Incorrect billing address	Verify whether the mobile device i s normal.
MK:0084	China M obile	HLR response: receipt of unexpect ed response	Provide the phone number to SM S Helper and submit a ticket to ve rify with operator.
MB:0088	China M obile	Operater's internal error	None
MI00036	China M obile	Operater's internal error	None
DB00144	China M obile	Target number is blocked by the global blacklist.	None
MA:0073	China M obile		Provide the phone number to SM S Helper and submit a ticket to ve rify with operator.
MI:0099	China M obile	vmsc response: receipt of unexpec ted response	Verify whether the mobile device i s normal.



Error Code	Category	Reason	Solution
MI:0089	China M obile	Operater's internal error	None
MI:0063	China M obile	Operater's internal error	None
MI:0090	China M obile	vmsc response: remote address is unreachable	Verify whether the mobile device i s normal.
MN00013	China M obile	The Mobile device is out of servic e.	Verify whether the mobile device i s normal.
DB:0107	China M obile	Operater's internal error	None
IB:0255	China M obile	Operater's internal error	None
MA:0022	China M obile	Operater's internal error	None
IB:0013	China M obile	Operater's internal error	None
MA:0001	China M obile	Operater's internal error	None
MK:0065	China M obile	No response from GIW due to tim	None
MN:0009	China M obile	Operater's internal error	None
UNKNOWN	China M obile	Unknown SMS status	None
DB:0010	China M obile	Operater's internal error	None
MK:0021	China M obile	Operater's internal error	None
MI:0038	China M obile	Operater's internal error	None



Error Code	Category	Reason	Solution
MI:0052	China M obile	Roaming restriction	None
MK:0003	China M obile	Invalid user. User authentication f ailed when this SMS message is se nt. The possible reason is that MS C considers the authentication pa ssword of the mobile phone to be invalid. The error code is 3 in mai ntenance and test console and 9 in ETSI GSM 0902 protocol.	None
MK:0009	China M obile	User is out of the service area MW DSET.	None
MK:0051	China M obile	Operater's internal error	None
MK:0068	China M obile	Operater's internal error	None
DB:0106	China M obile	Service code error	None
MB:1031	China M obile	SMC response: the maximum num ber of deliveries exceeds the limit probably because the phone me mory is full.	Verify whether the mobile device i s normal.
MI:0048	China M obile	Operater's internal error	None
MK00011	China M obile	The SMS service is unavailable on the mobile device.	Verify whether the mobile device i s normal.
MK:0048	China M obile	Operater's internal error	None
MK:0056	China M obile	Operater's internal error	None
MK:0057	China M obile	Operater's internal error	None



Error Code	Category	Reason	Solution
MK:0088	China M obile	vmsc response: possible version m ismatch	None
TUIDING	China M obile	Operater's blacklist	None
HIGRISK	China M obile	Gateway blacklist	Contact SMS Helper to remove the number from the blacklist.
CA:0054	China M obile	China Mobile internal error	None
MN:0041	China M obile	The phone is powered off, tempor arily unavailable, or exceptional due to other reasons.	None
MK:0090	China M obile	The phone is powered off, tempor arily unavailable, or exceptional due to other reasons.	None
XL:169	China M obile	The number is invalid or does not exist.	None
MN:xxxx	China M obile	Error codes starting with M refer to Mobile, which are mostly cause d by the problems occurred in mobile device. Possible reasons include: powered off, out of service, poor signal, out of the service area, invalid number, etc.	None
MK:xxxx	China M obile	Error codes starting with M refer to Mobile, which are mostly caused by the problems occurred in mobile device. Possible reasons include: powered off, out of service, poor signal, out of the service area, invalid number, etc.	None



Error Code	Category	Reason	Solution
MI:xxxx	China M obile	Error codes starting with M refer t o Mobile, which are mostly cause d by the problems occurred in mo bile device. Possible reasons inclu de: powered off, out of service, po or signal, out of the service area, i nvalid number, etc.	None
TA:169	China M obile	Invalid number	None
TC:0001	China M obile	Number on the blacklist	Contact SMS Helper to solve the p roblem through communication.
TC:0007	China M obile	SMS message contains sensitive w ords.	Contact SMS Helper to solve the p roblem through communication.
12	China Un icom	Incorrect billing address (invalid n umber, out-of-service phone, pow ered-off phone, call restriction or user transferred to China Unicom Secretary)	Verify whether the mobile device i s normal.
1	China Un icom	The number is invalid or does not exist.	Verify whether the mobile device i s normal.
10	China Un icom	Incorrect Src_ID (invalid number, out-of-service phone, powered-of f phone, call restriction or user transferred to China Unicom Secretary)	Verify whether the mobile device i s normal.
24	China Un icom	Invalid billing number (no longer in use)	Verify whether the mobile device i s normal.
5	China Un icom	The number is out of service.	Verify whether the mobile device i s normal.
29	China Un icom	Mobile user information error	Verify whether the mobile numbe r is normal.



Error Code	Category	Reason	Solution
13	China Un icom	Business code is not assigned. The corresponding declaration item c annot be found according to the access number and service code in the MT bill.	Verify whether the mobile device is normal. If it is normal, contact C hina Unicom customer service to c onfirm whether the SMS service is activated.
93	China Un icom	Monthly rent authentication faile d (out of service or cancellation of account)	Verify whether the mobile device i s normal.
11	China Un icom	Operater's internal error	None
4	China Un icom	Powered off	Verify whether the mobile device i s normal.
54	China Un icom	Powered off	Verify whether the mobile device i s normal.
59	China Un icom	Operater's internal error	Provide the phone number to SM S Helper and submit a ticket to ve rify with operator.
15	China Un icom	Out of the service area	Verify whether the mobile device i s normal.
23	China Un icom	Operater's internal error	Provide the phone number to SM S Helper and submit a ticket to ve rify with operator.
27	China Un icom	SMS service is not supported.	Verify whether the mobile device is normal. If it is normal, contact C hina Unicom customer service to c onfirm whether the SMS service is activated.
W-BLACK	China Un icom	Number on the global blacklist	Provide the phone number to SM S Helper to remove the number fr om the blacklist.
17	China Un icom	Operater's internal error	None
51	China Un icom	Powered off	Verify whether the mobile device i s normal.



Error Code	Category	Reason	Solution
-37	China Un icom	Powered off	Verify whether the mobile device i s normal.
20	China Un icom	Out of service	Verify whether the mobile device i s normal.
55	China Un icom	Out of the service area	Verify whether the mobile device i s normal.
67	China Un icom	Invalid number	Verify whether the mobile device i s normal.
95	China Un icom	Authentication failed due to canc ellation or inexistence of account.	Verify whether the mobile device i s normal.
22	China Un icom	Operater's internal error	None
90	China Un icom	Operater's internal error	None
-74	China Un icom	Operater's internal error	None
2	China Un icom	Operater's internal error	None
104	China Un icom	Operater's internal error	None
92	China Un icom		Provide the phone number to SM S Helper and submit a ticket to ve rify with operator.
86	China Un icom	Out of the service area	None
50	China Un icom	Out of service	None
8	Unicom	Message length error	None
57	China Un icom	Operater's internal error	None



Error Code	Category	Reason	Solution
79	China Un icom	The memory is full.	Verify whether the mobile device i s normal.
53	China Un icom	Powered off	Verify whether the mobile device i s normal.
3	China Un icom	Operater's internal error	None
255	China Un icom		Provide the phone number to SM S Helper and submit a ticket to ve rify with operator.
100	China Un icom		Provide the phone number to SM S Helper and submit a ticket to ve rify with operator.
61	China Un icom	Invalid number	Verify whether the mobile device i s normal.
117	China Un icom		Provide the phone number to SM S Helper and submit a ticket to ve rify with operator.
45	China Un icom	Out of service	Verify whether the mobile device i s normal.
164	China Un icom		Provide the phone number to SM S Helper and submit a ticket to ve rify with operator.
46	China Un icom		Provide the phone number to SM S Helper and submit a ticket to ve rify with operator.
14	China Un icom	Operater's internal error	None
9	China Un icom	Invalid sequential number, including repetition, wrong format, etc.	Verify whether the mobile device i s normal.
69	China Un icom	User on the blacklist	None



Error Code	Category	Reason	Solution
89	China Un icom	Out of the service area	Verify whether the mobile device i s normal.
64	China Un icom	Out of the service area	Verify whether the mobile device i s normal.
88	China Un icom	Out of the service area	Verify whether the mobile device i s normal.
98	China Un icom	Out of service	Verify whether the mobile device i s normal.
18	China Un icom	User does not subscribe to the ser vice	Verify whether the mobile device is normal. If it is normal, contact C hina Unicom customer service to c onfirm whether the SMS service is activated.
36	China Un icom	Out of service	Verify whether the mobile device i s normal.
44	China Un icom	The SMS function is unavailable o n the mobile phone.	Verify whether the mobile device is normal. If it is normal, contact C hina Unicom customer service to c onfirm whether the SMS service is activated.
99	China Un icom	Out of service	Verify whether the mobile device i s normal.
43	China Un icom	The memory is full.	Verify whether the mobile device i s normal.
-43	China Un icom	The memory is full.	Verify whether the mobile device i s normal.
118	China Un icom	The SMS function is unavailable o n the mobile phone.	Verify whether the mobile device i s normal. If it is normal, contact C hina Unicom customer service to c onfirm whether the SMS service is activated.



Error Code	Category	Reason	Solution
52	China Un icom	The mobile device is incapable of receiving SMS messages.	Verify whether the mobile device i s normal. If it is normal, contact C hina Unicom customer service to c onfirm whether the SMS service is activated.
31	China Un icom	Invalid device.	Verify whether the mobile device i s normal. If it is normal, contact C hina Unicom customer service to c onfirm whether the SMS service is activated.
75	China Un icom	Number restriction	Verify whether the mobile device i s normal. If it is normal, contact C hina Unicom customer service to c onfirm whether the SMS service is activated.
103	China Un icom		Provide the specific mobile numb er to SMS Helper and submit a tic ket to verify with operator.
56	China Un icom	In arrears and out of service	Verify whether the mobile device i s normal.
106	China Un icom	Invalid fee. Authentication failed.	None
-1	China Un icom	Operater's internal error	None
19	China Un icom	User does not subscribe to the ser vice.	None
148	China Un icom	Operater's internal error	None
48	China Un icom	Operater's internal error	None
63	China Un icom	Operater's internal error	None
73	China Un icom	Operater's internal error	None




Error Code	Category	Reason	Solution
70	China Un icom	The mobile number is out of the s ervice area.	Verify whether the mobile device i s normal.
32	China Un icom	Operater's internal error	None
40	China Un icom	Operater's internal error	None
110	China Un icom	Operater's internal error	None
116	China Un icom	Operater's internal error	None
21	China Un icom	Operater's internal error	None
219	China Un icom	SMS messages cannot be received because the user's mobile device i s powered off, out of service, tem porarily unavailable, or exception al due to other reasons.	None
182	China Un icom	User's mobile device is temporaril y out of service.	None
124	China Un icom	User's mobile device is powered o ff, restricted from calling, tempora rily out of service, or exceptional due to other reasons.	None
101	China Un icom	Mobile number is invalid.	None
105	China Un icom	The phone is powered off, restrict ed from calling, temporarily out of service, or exceptional due to other reasons.	None
213	China Un icom	The phone is powered off, restrict ed from calling, temporarily out of service, or exceptional due to other reasons.	None




Error Code	Category	Reason	Solution
72	China Un icom	145 number segment is not invali d or does not exist	None
LT:0002	China Un icom	Connection failed due to poor sig nal. In case of batch delivery failur e that may be caused by sensitive words, you need to verify with op erator.	None
UNDELIV_60 1	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
EXPIRED_60 2	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device is normal.
UNDELIV_64 0	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
REJECTD_00 6	China Te lecom	SMS message is rejected for some reason.	Verify whether the message is bus iness SMS message. If so, contact China Telecom customer service t o confirm whether the SMS servic e is activated.
UNDELIV_70 5	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
EXPIRED_76 0	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device is normal.
EXPIRED_60 1	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.




Error Code	Category	Reason	Solution
UNDELIV_86 9	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_99 9	China Te lecom		Provide the specific mobile numb er to SMS Helper and submit a tic ket to verify with operator.
UNDELIV_60 2	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device is normal.
UNDELIV_61 4	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
EXPIRED_66 0	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_71 3	China Te lecom		Provide the specific mobile numb er to SMS Helper and submit a tic ket to verify with operator.
UNDELIV_61 5	China Te lecom		Provide the specific mobile numb er to SMS Helper and submit a tic ket to verify with operator.
EXPIRED_70 2	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
EXPIRED_64 0	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.



Error Code	Category	Reason	Solution
REJECTD_70 6	China Te lecom	SMS message is rejected for some reason.	Verify whether the message is bus iness SMS message. If so, contact China Telecom customer service t o confirm whether the SMS servic e is activated.
EXPIRED_61 5	China Te lecom	SMS message is rejected for some reason.	Verify whether the mobile device i s normal.
UNDELIV_76 5	China Te lecom		Provide the specific mobile numb er to SMS Helper and submit a tic ket to verify with operator.
UNDELIV_87 0	China Te lecom	Operater's internal error	None
UNDELIV_89 9	China Te lecom		Provide the specific mobile numb er to SMS Helper and submit a tic ket to verify with operator.
EXPIRED_00 1	China Te lecom		Provide the specific mobile numb er to SMS Helper and submit a tic ket to verify with operator.
UNDELIV_61 2	China Te lecom		Provide the specific mobile numb er to SMS Helper and submit a tic ket to verify with operator.
UNDELIV_71 4	China Te lecom		Provide the specific mobile numb er to SMS Helper and submit a tic ket to verify with operator.
UNDELIV_70 2	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_81 5	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional due to other reasons.	Verify whether the mobile device i s normal.



Error Code	Category	Reason	Solution
UNDELIV_77 1	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_71	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_62 7	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_81	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_66 0	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
EXPIRED_61	China Te lecom	Operater's internal error	None
UNDELIV_61	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_61 9	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_68 0	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.



Error Code	Category	Reason	Solution
UNDELIV_63 6	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_72 6	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_71 8	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_88 0	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_63 4	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
EXPIRED_01 0	China Te lecom	SMS message expired	No response from the mobile devi ce due to timeout
EXPIRED_61 9	China Te lecom	SMS message expired	No response from the mobile devi ce due to timeout
EXPIRED_99 9	China Te lecom	SMS message expired	No response from the mobile devi ce due to timeout
UNDELIV_00 1	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.
UNDELIV_62 0	China Te lecom	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional du e to other reasons.	Verify whether the mobile device i s normal.



Error Code	Category	Reason	Solution
EXPIRED_61 4	China Te lecom	Operater's internal error	None
EXPIRED_61	China Te lecom	Operater's internal error	None
EXPIRED_61	China Te lecom	Operater's internal error	None
EXPIRED_61	China Te lecom	Operater's internal error	None
UNDELIV_70 1	China Te lecom	Invalid number, out-of-service ph one or powered-off phone	None
UNDELIV_70 1	China Te lecom	Invalid number, out-of-service ph one or powered-off phone	None
UNDELIV_80 2	China Te lecom	Invalid number, out-of-service ph one or powered-off phone	None
UNDELIV_80	China Te lecom	Invalid number, out-of-service ph one or powered-off phone	None
UNDELIV	China Te lecom/C hina Uni com	SMS messages cannot be received because user's phone is out of ser vice, suspended or exceptional due to other reasons.	None
MOBILE BL ACK	China Te lecom/C hina Uni com	Number on the global blacklist	Contact SMS Helper to remove th e number from the blacklist.
Other	China Te lecom/C hina Uni com	Reason not announced by operat or	Provide the phone number to SM S Helper and submit a ticket to ve rify with operator.